

AJ-VXI-RAM

PIR detector with Ajax transmitter
868MHz Jeweller Wireless
Double PIR / Detection 12 m
Antimasking / Pet immunity
Reach in open space 1600 m
Outdoor use



Ajax
Optex outdoor detector with Ajax radio transmitter
868MHz Jeweller Wireless
Double PIR with antimasking
Detection: Range 12 m / 90°
Motion detection indicator
Tamper-resistant opening
Transmitter reach in open space 1600 m
Power through the transmitter at 3 V
Outdoor use
Degree of protection IP55
Total integration with Ajax alarm system

Specifications

Brand	Ajax
Devices	OPTEX detector with AJ-TRANSMITTER
Technology	Double volumetric PIR
PIR lens	16 zones
Detection range	12 m / 90° / Installation 1.2 m
Frequency	868 MHz Jeweller
Transmission distance	? 1600 m in open space
Pet immunity	Available
Masking	Available
Sensitivity	Adjustable. 3 levels (high, medium, low)
Tamper-resistant opening	Available
LEDs indication	Alarm, tamper, signal
Power supply	3 V through AJ-TRANSMITTER
Temp. operation	-20 °C ~ 60 °C
Degree of protection	IP55
Dimensions	186 (H) x 71.3 (W) x 105.5 (D) mm
Dimensions	500 g